

cry baby[®]
GARY CLARK JR.



BASIC OPERATION

POWER

The Gary Clark Jr. Cry Baby® Wah is powered by one 9-volt battery (remove bottom plate to install), the Dunlop ECB003 9-volt adapter, or the DC Brick™, Iso-Brick™, and Mini Iso-Brick™ power supplies.

OPERATION

1. Run an instrument cable from your guitar to the GCJ95's INSTRUMENT jack and another instrument cable from the GCJ95's AMPLIFIER jack into your amplifier's input.
2. Push the toe of the pedal down until you feel a “click” to turn the pedal on/off.
3. Rock your foot back and forth on the pedal to hear the vocal, expressive tones that the Cry Baby Wah is famous for.

SPECIFICATIONS

IMPEDANCE

Input Impedance	800K
Output Impedance	10K

FILTER PARAMETER

Heel Down	320 Hz to 390 Hz
Toe Down Fine Tune Max	1700 Hz to 2070 Hz
Toe Down Fine Tune Min	1050 kHz to 1270 Hz

MAXIMUM LEVEL

Input	-8.0 dBV
Output	+10 dBV

MAXIMUM GAIN AT CENTER FREQUENCY

Heel Down	+17dB @ 400Hz ~ 500Hz
Toe Down	+17dB @ 2.0kHz ~ 2.2kHz

Power Requirements	900 μ A @9V DC (8.1mW no load)
--------------------	------------------------------------